

Product Highlights

USB 2.0 Plug and Play

Can be used right away without requiring any configuration

True 10/100 mbps Network Connectivity

Create a fast, reliable wired connection to your network by simply plugging it into your PC

Dynamic Power Management

Reduces power usage during light traffic or when Ethernet cable is unplugged



DUB-E100

Hi-Speed USB 2.0 Fast Ethernet Adapter

Features

Connectivity

- RJ-45 (10/100 Mbps) port
- USB 2.0 port with attached USB Type A connector

Energy Saving

- Energy-saving suspend/resume function

Plug-and-Play installation

- Compatible with Windows 8/7/Vista/XP and Mac OS 10.5 to 10.10, and Linux

The DUB-E100 Hi-Speed USB 2.0 Fast Ethernet Adapter is a high-speed adapter that plugs into any available USB port on your computer to enable you to connect to an Ethernet network. The adapter eliminates the need to open your computer to install a network card, and it also lets you keep your notebook's expansion slot free for other uses.

Easy to Install and Use

The DUB-E100 Hi-Speed USB 2.0 Fast Ethernet Adapter connects to your computer's USB port and is ready to run almost as soon as it's plugged in. There is no need to change any configuration settings on your computer as the drivers install automatically after you insert the DUB-E100 CD. For extra convenience, the adapter's USB connector can be folded into the body, allowing it to be even more compact when not in use and being carried around.

Energy Saving

The DUB-E100 supports an energy-saving suspend and resume function to minimize power consumption, which is especially useful for notebook users as it helps conserve battery life, allowing them to use their notebooks for a longer period. Power is provided directly by the USB bus, eliminating the need for an external AC power adapter.

DUB-E100 Hi-Speed USB 2.0 Fast Ethernet Adapter

Technical Specifications

General

Standards	<ul style="list-style-type: none">• USB Specification Version 2.0• USB Specification Version 1.1• USB Specification Version 1.0• OHCI (Open Host Controller Interface)• EHCI (Enhanced Host Controller Interface)	<ul style="list-style-type: none">• IEEE 802.3 Ethernet• IEEE 802.3u 100BASE-T, TX, and T4 compatible• Supports suspended mode and remote wakeup• Supports full and half duplex in Fast Ethernet• device interfaces
Device Interfaces	<ul style="list-style-type: none">• USB Type A connector	<ul style="list-style-type: none">• RJ-45 (10/100 Mbps Dual-Speed)
Minimum System Requirements	<ul style="list-style-type: none">• Operating System: Microsoft Windows 8/7/Vista/XP SP3, Mac OS 10.5 to 10.10, and Linux	
Configuration/Management	<ul style="list-style-type: none">• Advanced Power Management reduces power usage during idle or light traffic periods	

Physical

LED	<ul style="list-style-type: none">• Power/LinkLAN	<ul style="list-style-type: none">• Tx/Rx Traffic
Power	<ul style="list-style-type: none">• Bus Powered 0.5 A, 5 V DC	
Power Consumption	<ul style="list-style-type: none">• 150 mA, 3.3 V DC	
Dimensions (L x W x H)	<ul style="list-style-type: none">• 73 x 21.3 x 20 mm (2.87 x 0.84 x 0.79 inches)	
Weight	<ul style="list-style-type: none">• 22 g (0.05 pounds)	
Operating Temperature	<ul style="list-style-type: none">• 0 °C to 40 °C (32 °F to 104 °F)	
Storage Temperature	<ul style="list-style-type: none">• -10 °C to 70 °C (14 °F to 158 °F)	
Operating Humidity	<ul style="list-style-type: none">• 5% to 95%, non-condensing	
Storage Humidity	<ul style="list-style-type: none">• 0% to 95%, non-condensing	
Certifications	<ul style="list-style-type: none">• CE• C-Tick	<ul style="list-style-type: none">• FCC Class B



For more information: www.dlink.com

D-Link European Headquarters. D-Link (Europe) Ltd., D-Link House, Abbey Road, Park Royal, London, NW10 7BX.
Specifications are subject to change without notice. D-Link is a registered trademark of D-Link Corporation and its overseas subsidiaries.
All other trademarks belong to their respective owners. ©2016 D-Link Corporation. All rights reserved. E&OE.

Updated February 2016

D-Link[®]
Home is where the **SMART** is