



Document: How to configure your D-Link modem (DSL-320T, DSL-320B) with BeThere ISP.
Date: 6-Nov-08

How to configure BETHERE ISP line using modem (DSL-320T, DSL-320B) and router (DIR-635, DIR-655, DIR-855).

- 1) The modem needs to be configure in 1483 Bridged IP LLC mode with VPI: 0 and VCI: 101 (VCI and VPI are specific for BETHERE ISP)



2) Configure your router using Manual Internet Connection Settings




3) Next step depends on the type of connection provided by BeThere.
You have to choices

- 1) Static IP
- 2) Dynamic IP

3a) Static IP

- Choose Static IP in Internet Connection Type
- Type in your connection details (IP address, Subnet mask, Default gateway, Primary DNS server, Secondary DNS server).



- Click Save Settings to apply.

3b) Dynamic IP

- Choose Dynamic IP in Internet Connection Type
- No more settings necessary

Product Page: DIR-655 Hardware Version: A3 Firmware Version: 1.11EU

D-Link

DIR-655 // SETUP ADVANCED TOOLS STATUS SUPPORT

INTERNET

WIRELESS SETTINGS

NETWORK SETTINGS

English

WAN

Use this section to configure your Internet Connection type. There are several connection types to choose from: Static IP, DHCP, PPPoE, PPTP, L2TP, and BigPond. If you are unsure of your connection method, please contact your Internet Service Provider.

Note : If using the PPPoE option, you will need to remove or disable any PPPoE client software on your computers.

Save Settings Don't Save Settings

INTERNET CONNECTION TYPE

Choose the mode to be used by the router to connect to the Internet.

My Internet Connection is: Dynamic IP (DHCP)

DYNAMIC IP (DHCP) INTERNET CONNECTION TYPE :

Use this Internet connection type if your Internet Service Provider (ISP) didn't provide you with IP Address information and/or a username and password.

Host Name :

Use Unicasting : (compatibility for some DHCP Servers)

Primary DNS Server :

Secondary DNS Server :

MTU : 1500 (bytes) MTU default = 1500

MAC Address :

Clone Your PC's MAC Address

WIRELESS

Copyright © 2004-2007 D-Link Systems, Inc.

- Click Save Settings to apply.