

How can I register with mydlink on my DIR-845L

Step 1: Log into you device using it's IP address, for example:

192.168.0.1	
-------------	--

Step 2: Click on "SETUP"

Product Page : DIR-845	L			Hardware Version : A1	Firmware Version : 1.02	
		177 27				
DIR-845L	SETUP	ADVANCED	TOOLS	STATUS	SUPPORT	
INTERNET	MYDLINK SETTINGS					
WIRELESS SETTINGS	Setting and registering	your product with mydlink (vill allow you to use its	mydlink cloud services		
NETWORK SETTINGS	features, including onl	ine access and management	of your device throug	h mydlink portal website.		
PARENTAL CONTROL	MYDLINK					
STORAGE	-	1	10.5			
MEDIA SERVER	mydlink Service : Non-Registered					
IPV6	myd					
MYDLINK SETTINGS	REGISTER MYDLINK SERVICE					
		Register my	dink Service			
			6			
WIRELESS						
		Copyright © 2012 D-Link Co	poration. All rights res	erved.		

Step 3: Click on "MYDLINK SETTINGS"

Product Page : DIR-845				Hardware Version : A1	Firmware Version : 1.02
D=HIII					
	2				
DIR-845L	SETUP	ADVANCED	TOOLS	STATUS	SUPPORT
INTERNET	MYDLINK SETTING				
WIRELESS SETTINGS	Setting and registerin	g your product with mydlink v	will allow you to use its	mydlink cloud services	
NETWORK SETTINGS	features, including on	line access and management	of your device throug	h mydlink portal website.	4
PARENTAL CONTROL	MYDLINK				
STORAGE	and the second se				
MEDIA SERVER	mydi	ink Service : Non-Registe	red		
IPV6	myc	llink E-mail :			
MYDLINK SETTINGS	REGISTER MYDLIN	K SERVICE			
	· ·	Desider	an 1. e		
		Register my	dirik service		
WIRELESS					
		Copyright © 2012 D-Link Co	rporation. All rights re:	served.	



You will notice (from the above image) the router isn't registered to any account

Step 4: Click on "Register mydlink Service"

Product Page : DIR-845L	Hardware Version : A1 Firmwa	re Version : 1.02
		1
Delink		
	Language : English	
MYDLINK RE	GISTRATION	
This device i through the your networ notifications You can regi create one r	s mydlink-enabled, which allows you to remotely monitor and manage your network mydlink.com website, or through the mydlink mobile app. You will be able to check k speeds, see who is connected, view device browsing history, and receive about new users or intrusion attempts. ster this device with your existing mydlink account. If you do not have one, you can now.	
	Do you have mydlink account? Ves, I have a mydlink account. No, I want to register and login with a new mydlink account.	
WIRELESS		3
	Copyright © 2012 D-Link Corporation. All rights reserved.	

Step 5: Here you will be presented with **<u>two options</u>** based upon the following question:

Do you have mydlink account?

- 1. Yes, I have mydlink account.
- 2. No, I want to register and login with a new mydlink account.



Option 1:

Step 6: Click on "Yes, I have mydlink account"

Product Page : DIR-845L	Hardware Version : A1	Firmware Version : 1.02
D-Link		
	Language : En	glish
MYDLINK REGISTRATION E-mail Address (Account Name) : @gmail.con Password : Skip Prev Login		
WIRELESS		
Copyright © 2012 D-Link Corporation. All rights r	eserved.	

Enter the following details:

```
E-mail Address (Account Name)
Password
```

Click on "Login"

You should be re-directred so you can login to your mydlink account

Devices					
DIR-845L 22643314	Router Status	Settings			
•9 <u> </u>	(((p)) ((p)) (0003	о . Пкърз	Model Name Network Name(SSID) Internet IP LAN IP Connected Devices	DIR-845L dlink-COD0 (2 dlink-COD2-m 192.168.77.1 192.168.0.1 30 device(s)	.4 GHz) edia (5 GHz) 62
	• 0000	J. IKbps			Reboot
	Connection L	J. IK bps ist Device Name	IP Address	MAC Address	Reboot Block
	Connection U	J. IK bps ist Device Name Uk1-MM-03010	IP Address 192.168.0.27	MAC Address C0:A0:88:58:87:88	Reboot Block
	Connection U Device	J. IK bps ist Device Name UKI-MM-03010	IP Address 192.168.0.27 192.168.1.200	MAC Address C0:40:88:58:87:88 F0:70:68:D6:58:E1	Reboot Block
	Connection U Device	J. IK bps ist Device Name UKI-MM-03010	IP Address 192.168.0.27 192.168.1.200 192.168.1.138	MAC Address C0:A0:89:58:87:88 F0:7D:68:06:58:E1 F0:7D:68:0C:35:E8	Block
		J. I K bp s ist Device Name UKI-MM-02010	IP Address 192.168.0.27 192.168.1.200 192.168.1.138 192.168.1.24	MAC Address C0:A0:B8:S8:87:88 F0:7D:68:D6:S8:E1 F0:7D:68:0C:35:E8 F0:7D:68:C8:59:43	Block
	Connection D Device	J. I K bp s Ist Device Name URI-MM-03010	1P Address 192.168.0.27 192.168.1.200 192.168.1.738 192.168.1.24 192.168.1.24	MAC Address C0:A0:88:58:87:88 F0:7D:68:06:58:E1 F0:7D:68:0C:35:E8 F0:7D:68:C8:59:43 D6:89:77:13:85:60	Reboot Block O O O O
	Connection U	J. I K bp s ist Device Name URI-MM-03010	19 Address 192.168.0.27 192.168.1.200 192.168.1.28 192.168.1.24 192.168.1.24 192.168.1.202	MAC Address C0:A0:88:58:87:88 F9:70:68:06:59:81 F0:70:68:06:23:58 F0:70:68:06:23:58 F0:70:68:06:39:43 D0:89:77:13:85:60 10:78:E3:10:13:76	Block O O O O O O O O O O O O

Once logged in, accept any messages which may popup, such as JAVA.



Option 2:

Step 7: Click on "No, I want to register and login with a new mydlink account."

Product Page : DIR-845L	Hardware Version : A1 Firmware Version : 1.02
D-Link	Language : English
MYDLINK REGISTRATION	
Please fulfill the options to complete th E-mail Address (Account Name) : Password : Confirm Password : Last name : First Name : I Accept the mydlink terms an	nd conditions.
Skip Prev Sign up WIRELESS Copyright © 2012 D-Link Corporation. All ri	ghts reserved.

Enter the following details:

E-mail Address (Account Name)
Password
Confirm Password
Last name
First Name

Click inside the box <code>`I</code> accept the mydlink terms and conditions", then click on <code>`Sign up"</code>

Step 8: You should receive the following messages



Please check the account you have used for confirmation instructions

Click on "Aceptar"





You will now be presented with the above message. Click on "Aceptar"

Step 9: You can finally check by clicking on SETUP – MYDLINK SETTINGS

Product Page : DIR-845	Ľ,			Hardware Version : A1	Firmware Version : 1.02
D-Lini	¢				\prec
DIR-845L	SETUP	ADVANCED	TOOLS	STATUS	SUPPORT
INTERNET	MYDLINK SETTINGS				
WIRELESS SETTINGS	Setting and registering	your product with mydlink v	vill allow you to use its	s mydlink cloud services	
NETWORK SETTINGS	features, including onli	ne access and management	of your device through	h mydlink portal website.	
PARENTAL CONTROL	MYDLINK				
STORAGE		-h Carrier - Carlebrard			
MEDIA SERVER	myan	Ink Service : Registered	amail com		
IPV6	mya	inik E-mail : @	ymail.com		
MYDLINK SETTINGS	REGISTER MYDLINE	(SERVICE			
		Register my	dlink Service	\mathcal{I}	
WIRELESS					
		Copyright © 2012 D-Link Cor	poration. All rights res	served.	

You will now see "Registered" and an email address present. Due to the device has been registered to the email you have selected, the "**Reister mydlink Service**" will be greyed out.

End of Document