

## How to configure SharePort Mobile?

Note: If using a D-Link Mobile router, SharePort Mobile is only compatible in Router and Wi-Fi-Hotspot Mode

Step 1: Insert your USB Flash Drive into your router

The default username is admin and the password is blank (nothing). Click Login.

ogin to the router :			
	User Name : Admin		
	Password :	Login	

Step 3: Click the Setup tab then click Storage on the left side

Step 4: Check Enable SharePort Web Access and ensure Allow Remote Access is checked, and then click Save Settings

D-Link							
//	SETUP	ADVANCED	TOOLS	STATUS	SUPPORT		
INTERNET WIRELESS SETTINGS NETWORK SETTINGS STORAGE MEDIA SERVER IPV6 MYDLINK SETTINGS	STORAGE Web File Access allows you to or USB storage drive plugged Access checkbox, then use to your storage devices. After p appear in the list with a link to with a user account. Save Settings Don't Save : SHAREPORT WEB ACCESS Enable SharePort Web Acc HTTP Access I HTTPS Access I Allow Remote Acc	o use a web browse d into the router. To the Admin account o blugging in an SD car to it. You can then u Settings xcess : Port : 8181 Port : 4433 xcess :	er to remotely access files o use this feature, check i or create user accounts tr rd or USB storage drive, t use this link to connect to	stored on an SD card the Enable Web File o manage access to he new device will o the drive and log in	Helpful Hints • The Storage page contains information about the USB storage drivers or SD cards currently plugged into the device. • More		
	USER CREATION User N Passw	lame :	<< User Nan	ne 💌			

## Mobile Setup





Step 5: Download the SharePort<sup>™</sup> Mobile App from App Store or Google Play

Step 6: Ensure your mobile device is connected to the wireless network (SSID) of your SharePort<sup>TM</sup> Mobile supported router.

Step 7: Launch the SharePort<sup>™</sup> Mobile app; the following screen will appear. Note that iOS may look slightly different.

## How to configure SharePort Mobile?





Step 8: Click Settings





Step 9: Enter your username and password Note: By default the username is set to "admin" with no password.

Step 10: Change the port if required (by default it is configured at port 8181 within the router configuration)

Note: If accessing content over Internet, enter the IP or Domain address of your router; if accessing locally, it will fill in automatically.





## How to configure SharePort Mobile?



SharePort Mobile is successfully configured and your USB media should now be accessible.

v₽ ►	· · · · · · · · · · · · · · · · · · ·	ЧЦ∥ '중' "Щ 🛀 4:26 рм			
	Music				
		Q			
5	01 La Voce del Silenzio (The Voice of Silence), song.mp3 11.3MB, 2010-12-10 13:30	*			
5	<b>02 Sogno, song.mp3</b> 9.2MB, 2010-12-10 13:31	*			
-	03 II mare calmo della sera (The Calm Evening Sea), song.mp3 10.7MB, 2010-12-10 13:31	*			
5	04 Vivere (To Live), song.mp3 9.9MB, 2010-12-10 13:32	*			