

# 12

## D-Link DWL- 50AT Indoor Omni Antenna



Remove one default antenna from the wireless device and start to assemble!



D-Link's Omni Directional Antenna offers the most cost effective solution for extending the wireless LAN coverage area. The antenna is fully compatible with all products and can be used with any 2.40 to 2.4835 GHz products.

### Installation:

1. Remove the original antenna from your wireless device.
2. Screw the DWL-50AT RP- SMA connector into your wireless device.
3. Adjust the antenna to the suitable direction for extending the wireless coverage area.

Frequency band	2400-2500MHz
Antenna gain	5.0dBi Typical
VSWR	2.0:1 Max.
Polarization	Linear
HPBW / H-plane	Toroidal
HPBW / E-plane	60 degree
Impedence	50 Ohms nominal
Dimensions HxWxD	197 mm(length)
Weight	29.5gw